



CATALOG NO	VOLTAGE	NEC MOTOR HP	NEC MOTOR CURRENT	WATTS LOSS	APPROX. WEIGHT-LBS
KDRH22LC4	208/240	60	169	209	85
KDRH23HC4	208/240	60	169	220	85
KDRH43LC4	575/600	125	125	261	85
KDRH44LC4	575/600	150	144	253	85

NEC MOTOR CURRENTS SHOWN IN THE 208/240 VOLT CHART ARE BASED ON HORSE POWERS AT 208 VOLT. 575/600 VOLT CHART USE THE 575 VOLT CURRENT RATING.

 TRANS-COIL, INC MILWAUKEE, WI WWW.transcoil.com 800-824-8282	PERFORMANCE AND PROTECTION FOR DRIVES.	
	KDR Drive Reactor	
	CATALOG#	MOTOR HP AMPS
	3PH, 60Hz, 600V Max, <input type="checkbox"/> A Max. 40C Amb Max, 115C Rise	

ENCLOSURE LABEL PLACED ON FRONT COVER.

CUSTOMER IS RESPONSIBLE FOR INSTALLATION TO MEET ALL NATIONAL AND LOCAL ELECTRICAL CODES.

				TOLERANCES (EXCEPT AS NOTED) DECIMAL .XX ± .03 .XXX ± .01 FRACTIONAL ± 1/32 ANGULAR ± 1/2°		 7878 N. 86th STREET MILWAUKEE, WI 53224
				KDR (FRAME H) ENCLOSED WIDE RANGE REACTOR		
NO	REVISION	DATE	BY	DRN BY DSW	DATE 03/05/03	DWG. NO. B KDR-41DG SCALE 3/16"=1" APRVD.
						SHT. 1 OF 1