

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT	WEIGHT with Fuse Monitor
HGP0015CW1S0000	600	5	15	17	19.75	17.5	12.14	1	300	75	77
HGP0030CW1S0000	600	10	30	32	31.5	17.5	12.14	1	425	130	132
HGP0040CW1S0000	600	15	40	41	31.5	17.5	12.14	1	675	170	172
HGP0050CW1S0000	600	15	50	52	31.5	17.5	12.14	1	700	180	182
HGP0060CW1S0000	600	20	60	62	31.5	17.5	12.14	1	900	190	192
HGP0075CW1S0000	600	25	75	77	31.5	17.5	12.14	1	1000	195	197
HGP0100CW1S0000	600	30	100	99	31.5	17.5	12.14	1	1050	235	237
HGP0125CW1S0000	600	40	125	125	56	17.15	16.14	1	1200	308	310
HGP0150CW1S0000	600	45	150	144	56	17.15	16.14	1	1500	350	352
HGP0200CW1S0000	600	60	200	192	70	20	20	1	1850	500	502
HGP0250CW1S0000	600	75	250	242	70	20	20	1	2000	505	507
HGP0300CW1S0000	600	90	300	289	70	20	20	1	2500	675	677
HGP0350CW1S0000	600	105	350	336	70	20	20	1	2800	725	727
HGP0400CW1S0000	600	120	400	382	60	52	24.5	1	2700	990	992
HGP0450CW1S0000	600	135	450	412	60	52	24.5	1	3050	1200	1202
HGP0500CW1S0000	600	150	500	472	60	52	24.5	1	3000	1300	1302
HGP0600CW1S0000	600	180	600	576	60	52	24.5	1	3200	1400	1402

\*Note- Products with fuse monitor will have "G" replace "S" in part number