

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG8BW03ST	240	3	7.5	22	32.24	33	13.73	3R	200	125
HG10BW03ST	240	3	10	28	32.24	33	13.73	3R	225	128
HG15BW03ST	240	5	15	42	32.24	33	13.73	3R	300	135
HG20BW03ST	240	6	20	54	36	39.15	13.73	3R	350	187
HG25BW03ST	240	8	25	68	36	39.15	13.73	3R	375	192
HG30BW03ST	240	10	30	80	36	39.15	13.73	3R	450	197
HG40BW03ST	240	15	40	104	36	39.15	13.73	3R	675	198
HG50BW03ST	240	15	50	130	36	39.15	13.73	3R	700	210
HG60BW03ST	240	20	60	154	36	39.15	13.73	3R	800	220
HG75BW03ST	240	25	75	192	51	39.07	17.73	3R	900	347
HG100BW03ST	240	30	100	248	51	39.07	17.73	3R	1100	362