

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG8AW03ST	480	3	7.5	11	32.24	33	13.73	3R	200	105
HG10AW03ST	480	3	10	14	32.24	33	13.73	3R	200	112
HG15AW03ST	480	5	15	21	32.24	33	13.73	3R	275	125
HG20AW03ST	480	6	20	27	32.24	33	13.73	3R	300	126
HG25AW03ST	480	8	25	34	32.24	33	13.73	3R	325	144
HG30AW03ST	480	10	30	40	32.24	33	13.73	3R	375	150
HG40AW03ST	480	15	40	52	36	39.15	13.73	3R	625	220
HG50AW03ST	480	15	50	65	36	39.15	13.73	3R	650	229
HG60AW03ST	480	20	60	77	36	39.15	13.73	3R	825	239
HG75AW03ST	480	25	75	96	36	39.15	13.73	3R	950	249
HG100AW03ST	480	30	100	124	36	39.15	13.73	3R	975	269
HG125AW03ST	480	40	125	156	36	39.15	13.73	3R	1150	289
HG150AW03ST	480	45	150	180	51	39.07	17.73	3R	1450	400
HG200AW03ST	480	60	200	240	51	39.07	17.73	3R	1775	470
HG250AW03ST	480	75	250	302	51	45.14	21.73	3R	2050	547
HG300AW03ST	480	90	300	361	51	45.14	21.73	3R	2500	615
HG350AW03ST	480	105	350	414	51	45.14	21.73	3R	2725	665
HG400AW03ST	480	120	400	477	64	57.13	25.96	3R	3100	975
HG450AW03ST	480	150	450	515	64	57.13	25.96	3R	3350	984
HG500AW03ST	480	150	500	590	64	57.13	25.96	3R	3500	1000
HG600AW03ST	480	180	600	720	64	57.13	25.96	3R	3500	1224