

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG15CW03ST	600	5	15	17	32.24	33	13.73	3R	300	135
HG30CW03ST	600	10	30	32	32.24	33	13.73	3R	425	154
HG40CW03ST	600	15	40	41	36	39.15	13.73	3R	675	239
HG50CW03ST	600	15	50	52	36	39.15	13.73	3R	700	249
HG60CW03ST	600	20	60	62	36	39.15	13.73	3R	900	259
HG75CW03ST	600	25	75	77	36	39.15	13.73	3R	1000	269
HG100CW03ST	600	30	100	99	36	39.15	13.73	3R	1050	269
HG125CW03ST	600	40	125	125	36	39.15	13.73	3R	1200	289
HG150CW03ST	600	45	150	144	51	39.07	17.73	3R	1500	432
HG200CW03ST	600	60	200	192	51	39.07	17.73	3R	1850	480
HG250CW03ST	600	75	250	242	51	45.14	21.73	3R	2000	580
HG300CW03ST	600	90	300	289	51	45.14	21.73	3R	2500	736
HG350CW03ST	600	105	350	336	64	57.13	25.96	3R	2800	956
HG400CW03ST	600	120	400	382	64	57.13	25.96	3R	2700	966
HG450CW03ST	600	150	450	412	64	57.13	25.96	3R	3050	976
HG500CW03ST	600	150	500	472	64	57.13	25.96	3R	3000	1161
HG600CW03ST	600	180	600	576	64	57.13	25.96	3R	3200	1176
HG700CW03ST	600	210	700	672	64	57.13	25.96	3R	3600	1191
HG800CW03ST	600	240	800	768	64	57.13	25.96	3R	3900	1206
HG900CW03ST	600	270	900	864	64	57.13	25.96	3R	3800	1221