

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG8BW00STC	240	3	7.5	22	30.75	17	8	N/A	200	65
HG10BW00STC	240	3	10	28	30.75	17	8	N/A	225	68
HG15BW00STC	240	5	15	42	30.75	17	8	N/A	300	75
HG20BW00STC	240	6	20	54	30.75	17	8	N/A	350	95
HG25BW00STC	240	8	25	68	30.75	17	8	N/A	375	100
HG30BW00STC	240	10	30	80	30.75	17	9	N/A	450	105
HG40BW00STC	240	15	40	104	30.75	17	9.25	N/A	675	105
HG50BW00STC	240	15	50	130	56	17	9.25	N/A	700	130
HG60BW00STC	240	20	60	154	56	17	9.25	N/A	800	140
HG75BW00STC	240	25	75	192	56	17	9.25	N/A	900	200
HG100BW00STC	240	30	100	248	56	17	10.6	N/A	1100	210