

HG7 240V Open XM										
PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG8BW00XM	240	3	7.5	22	30.75	12	12	N/A	200	55
HG10BW00XM	240	3	10	28	30.75	17	12.5	N/A	225	70
HG15BW00XM	240	5	15	42	30.75	12	12	N/A	300	65
HG20BW00XM	240	6	20	54	30.75	17	12.5	N/A	350	100
HG25BW00XM	240	8	25	68	30.75	17	12.5	N/A	375	100
HG30BW00XM	240	10	30	80	30.75	17	12.5	N/A	450	100
HG40BW00XM	240	15	40	104	56	17	16.5	N/A	675	115
HG50BW00XM	240	15	50	130	56	17	16.5	N/A	700	130
HG60BW00XM	240	20	60	154	56	17	16.5	N/A	800	140
HG75BW00XM	240	25	75	192	56	17	16.5	N/A	900	200
HG100BW00XM	240	30	100	248	-	-	-	N/A	1100	-
HG7 240V Type 1 XM										
PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT
HG8BW01XM	240	3	7.5	22	31.5	17.5	12.14	1	200	115
HG10BW01XM	240	3	10	28	31.5	17.5	12.14	1	225	120
HG15BW01XM	240	5	15	42	31.5	17.5	12.14	1	300	125
HG20BW01XM	240	6	20	54	31.5	17.5	12.14	1	350	145
HG25BW01XM	240	8	25	68	31.5	17.5	12.14	1	375	150
HG30BW01XM	240	10	30	80	31.5	17.5	12.14	1	450	155
HG40BW01XM	240	15	40	104	56	17.15	16.14	1	675	195
HG50BW01XM	240	15	50	130	56	17.15	16.14	1	700	205
HG60BW01XM	240	20	60	154	56	17.15	16.14	1	800	220
HG75BW01XM	240	25	75	192	56	17.15	16.14	1	900	253
HG100BW01XM	240	30	100	248	56	17.15	16.14	1	1100	285